

NOSTRADAMUS

S e r v i c e M a n u a l

FACE CO., LTD.


JAMMA STANDARD

SOLDER SIDE			PARTS SIDE
GND	A	1	GND
GND	B	2	GND
+5V	C	3	+5V
+5V	D	4	+5V
	E	5	
+12V	F	6	+12V
	H	7	
COIN COUNTER 2	J	8	COIN COUNTER 1
	K	9	
SPEAKER(-)	L	10	SPEAKER(+)
	M	11	
VIDEO GREEN	N	12	VIDEO RED
VIDEO SYNC	P	13	VIDEO BLUE
SERVICE SW	R	14	VIDEO GND
	S	15	TEST SW
COIN SW 2	T	16	COIN SW 1
START SW 2	U	17	START SW 1
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Y	21	1P RIGHT
2P PUSH 1	Z	22	1P PUSH 1
2P PUSH 2	a	23	1P PUSH 2
2P PUSH 3	b	24	1P PUSH 3
	c	25	
	d	26	
GND	e	27	GND
GND	f	28	GND


■ BOARD CONNECTOR
JAMMA STANDARD

■ CRT MONITOR SCREEN
VERTICAL SCREEN
DISPLAY

■ CONTROL PANEL



8-DIRECTION
LEVER



ENERGY
CHARGED
BY PUSHING
FIRE BUTTON
E.B.A ENERGY
CHARGER

■ TWO PEOPLE CAN PLAY
SIMULTANEOUSLY
YOU CAN JOIN MID-GAME

DIP SWITCH

DIP SWITCH 1		1	2	3	4	5	6	7	8
NUMBER OF PLAYERS	3	OFF	OFF						
	2	ON	OFF						
	4	OFF	ON						
	5	ON	ON						
DIFFICULTY	NORMAL			OFF	OFF				
	EASY			ON	OFF				
	HARD			OFF	ON				
	HARDEST			ON	ON				
SCREEN	NORMAL					OFF			
	TURNUED					ON			
DEMONSTRATION SOUNDS	ON						OFF		
	OFF						ON		
EXTENDED PLAY	800,000/1,500,000 SCORES							OFF	OFF
	500,000/1,000,000 SCORES							ON	OFF
	1,000,000/2,000,000 SCORES							OFF	ON
	NO							ON	ON
UPON SHIPPING		OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF

[illegible]

TEST MODES

Test patterns will appear on CRT monitor screen if you put on 2-8 dip switch.

Furthermore, by pressing service switch, the following modes will appear.

- SWITCH TEST
- DIP SWITCH DISPLAY
- SOUND TEST
- BG CHARACTER TEST
- SPRITE TEST

FACE co., LTD.

1 - 9 - 8 YAYOI-CHO NAKANO-KU TOKYO 164 JAPAN

TEL 03 (3 3 7 2) 7 7 6 6

FAX 03 (3 3 7 2) 7 8 5 5